

SUREPORT DATA SHEET

Foundry/Brocade-Compatible Dual Fiber XFP



Champion ONE's Dual Fiber XFP product line supports a variety of protocols over a wide range of distance and temperature options. These optics are fully MSA-compliant and offer direct compatibility with your existing switches and routers.

Champion ONE Sureport transceivers are programmed for one-to-one compatibility with your existing OEM platforms.

Technical Specifications

STANDARDS AND REGULATORY COMPLIANCE

RoHS compliant
 XFP MSA (multi-source agreement)
 IEEE Std 802.3
 Fibre Channel Draft Physical Interface Specification
 Compliant with SONET/SDH optical standards
 UL/CSA Class 3862.07 / 3862.87

PROTOCOLS AND DATA RATES

SONET OC-192
 10G Ethernet LAN/WAN
 10G Fibre Channel
 ITU-T G.709
 10GBASE LAN/WAN + FEC
 10G FC and FEC

DIMENSIONS

71 x 18.5 x 8.5 mm ; 300 g

CONNECTOR

Duplex LC connector

WARRANTY

All feature a limited 5-year warranty

C1 Part Number	Transmit Wavelength (nm)	Fiber Type	Rated Distance (km)	Temp Range (°C)	Description	Tx (min/max) (dBm)	Rx (min/max) (dBm)	Substitute for Foundry-Brocade® Part #(s)
MULTI-RATE 10G DUAL FIBER XFP								
10GEXFP-SR-FBR	850	MMF	.03	0 to 70	30m 10GBase-SR/SW, 10G FC, OC-192 XFP, Foundry/Brocade compatible	-7.3 / -1.2	-9.9 / -1.0	OC192-XFP-SR1 10G-XFP-1310-LRM 10G-XFP-SR
10GEXFP-LR-FBR	1310	SMF	10	0 to 70	10km 10GBase-LR/LW, 10G FC, OC-192 XFP, Foundry/Brocade compatible	-6.0 / -1.0	-11.0 / 0.5	10G-XFP-LR
10GEXFP-ER-FBR	1550	SMF	40	0 to 70	40km 10GBase-ER/EW, 10G FC, OC-192 XFP, Foundry/Brocade compatible	-1.0 / 2.0	-14.0 / -1.0	10G-XFP-ER
10GEXFP-ZR-FBR	1550	SMF	80	0 to 70	80km 10GBase-ZR/ZW, 10G FC, OC-192 XFP, Foundry/Brocade compatible	0.0 / 4.0	-24.0 / -7.0	10G-XFP-ZR

* Parts are intended as one-to-one replacements. Please verify that the OEM part number is compatible with your system before ordering. If you have questions regarding specific switches and routers, please contact your Champion ONE sales representative for support. In most cases, a customized solution can be developed to meet your needs.